ThinkCentre Tiny-In-One 22 Gen3 10R1PAR1++

Region EMEA

Machine Type

10R1

Color Black

Display Size

21.5"

Multi-touch

None

Resolution

1920x1080

Aspect Ratio

16:9

Pixel Pitch 0.24795 mm

Dot / Pixel Per Inch

102.4 dpi

Brightness

250 nits

Contrast Ratio

1000:1

Pixel Response Time

4-14 ms

Color Gamut

72%

View Angle (H / V) 178 / 178

Stand

Adjustable Stand

Power Comsuption (Typical / Maximum)

19W / 32W

Power Supply 90W 88% Adapter

Warranty 3-year

Ann Date (mm/yy)

07/17

Note:

Country Code "US" is for United States, "++" is for EMEA countries (e.g. AD - Saudi, Arabia, AT - Austria, BM - Bulgaria, etc.), "xx" is for EAST countries (e.g. BM - Bulgaria, CX - Hungary, CY - Cyprus, etc.), and "**" is for MEA countries (e.g. AD - Saudi, Arabia, ED - Egypt, EQ - Sweden, etc.). Please be aware that the EMEA/ EAST/MEA models listed above might not be available in all countries



www.lenovo.com

This publication was developed for products and services offered in the United States and E.M.E.A countries. Lenovo may not offer the products, services or features discussed in this document in other countries. Lenovo may withdraw an offering at any time. Information is subject to change without notice. Consult your local representative for information on offerings available in your area. Lenovo reserves the right to change specifications or other product information without notice. Lenovo is not responsible for photographic or typographical errors. Lenovo provides this publication "as is" without warranty of any kind, either express or implied, including the implied warranties of merchantability or ftness for a particular purpose.



http://psref.lenovo.com

Visit psref website for the latest version of Product Specifications Reference.
© Lenovo, 2018. All rights reserved.



ThinkCentre Tiny-in-One (TIO) 22 Gen3

Model	Non-touch model: Touch model:	10R1PAR1++/10R1PAR1++/10R0PAR1++/10R0PAR1		ı		
Form factor			ience when optional Tiny slots into	1		
Compatible Tiny:		ean cabling and effortle 00 / M700 / M600 / M7	ess setup 15 / M93/p* / M83 / M73* / M53 /			
,	Chromebox Tiny	can't be turned on by	oressing power button of TIO	Ē		
Denel			• .	F		
Panel	Notes: In-Plane Sv	witching may refer to V	**, White LED backlight A, PLS, and IPS panels	L		
Viewable image size	21.5" (546.1mm) diagonal					
Max view area (W x H) Bezel Width	18.74" x 10.54" / 476.1mm x 267.8mm Top / Side: 2mm, Bottom: 22.1mm					
Native resolution	1920x1080					
Multi-touch	Optional 10-point multi-touch, supports Wake on Touch					
Aspect ratio Pixel pitch (mm)	16:9 0.24795mm					
Dot/Pixel per Inch	0.24795mm 102.4 dpi					
Brightness	250 nits or cd/m² (typical)					
Contrast ratio	1000:1 (typical)					
Pixel response time Color gamut	14ms (default), over drive to 4ms, 6ms 72%					
Anti-reflective Anti-glare						
Viewing angle at 10:1 CR178° (+/- 89°) horizontal, 178° (+/- 89°) vertical						
Preset resolutions	640x350 @ 70Hz	CCLI- 70LI- 75LI-				
	640x480 @ 60Hz, 720x400 @ 70Hz	66HZ, /2HZ, /5HZ				
	720x40 © 70H2 800x600 @ 60Hz, 72Hz, 75Hz 1024x768 @ 60Hz, 70Hz, 75Hz 1152x864 @75Hz 1280x800 @ 60Hz 1280x1024 @ 60Hz, 72Hz, 75Hz 1366x768 @ 60Hz					
	1440x900 @ 60Hz, 75Hz					
	1600x1200 @ 60H 1680x1050 @ 60H					
	1920x1080 @ 60H					
Presets / user settings	Presets: 25; user s					
On screen display On screen display with digital user controls (8 languages)						
Control features	Ftont: Exit butto	n, Left / Mode-switchin	g button (TIO / monitor mode), / Menu button, Power button			
		p button, Volume down				
Tiny-in-One Power On	Pressing Alt + P or	keyboard or pressing	Power button positioned on TIO			
Cido porto (TIO)	can turn on both TIO and Tiny (only some Tiny support, see compatible list)					
Side ports (TIO)	One USB 3.1 Gen1 / USB 2.0 (when M73 or M53 installed or USB 2.0 connected via USB upstream port) Notes: The USB port is only available when a Tiny is istalled or a PC is					
	connected	via USB upstream por	t			
Side ports (Tiny)	Side ports offered by installed Tiny (optional)					
Rear ports 3-in-1 Cable	One DisplayPort in port, one USB upstream port, one power connector Undetachable 3-in-1 cable (Power connecter, USB [supports USB 3.1 Gen1]					
· · · · · · · · · · · · · · · · · · ·	/ USB 2.01. Display	Port), only for connect	ing to Tiny installed (optional)			
Camera	720p camera with dual microphone for VOIP, LED indicator					
Internal Speaker	2 watt x2			ļ		
Security	security Security keyhole for attachment of optional cable lock (Kensington® lock compatible), locks optional Tiny with TIO together, more security features offered by Tiny installed (optional)					
Mechanical	Dimensions	TIO without stand	TIO with stand			
	W x D x H (inch)	19.26 x 2.85 x 13.35	19.26 x 10.76 x 14.59 - 18.93			
	W x D x H (mm)	489.3 x 72.5 x 339	489.3 x 273.3 x 370.7 - 480.7			
	Weight (Approx.)	7.01 lb / 3.19 kg	11.77 lb / 5.34 kg			
		<u> </u>				

	Mounting features	Wall or desk mounting using the extend arm or third-party accessories meeting the VESA FPMPMI® (100mm mount)
0	Adjustable stand	Tilt: 30° back, -5° forward; \\ lift: 4.3" (110mm); \\ swivel: +/-45°; \\ Pivot: clockwise 0° to 90°
	Power supply Power consumption	90 watts AC/DC adapter, 88% PSU, universal 19 watts typical, 32 watts maximum, <0.5 watts standby / suspend
	Limited warranty	3-years, Customer Carry-In or Mail-In via Rapid Replacement Service
	VESA-compliant Ergonomics Emission standards Environmental	VESA DDC2B/CI, VESA DPMS-compliant ISO 9241-307, TUV Eye Comfort certified FCC Class B TCO 7.0, TCO Edge 2.0, WEEE, RoHS, ENERGY STAR® 7.0, EPEAT™ Gold rating, ULE Gold, TUV, VOC
	Windows certifications	Windows 7 and Windows 10 certified
	Ship group	TIO (Monitor), detachable stand, AC/DC power adapter, power cord, user's guide and driver CD, quick start and safety poster
	Accessories	For compatible accessories, please go to http://www.lenovoquickpick.com
	·	

ThinkCentre Tiny-in-One 22 Gen3 Compatible list							
Model	M910 / M710 / M900 / M700 /	M93/p Tiny,	Chromebox				
	M600 / M715 / M83 / M53 Tiny	M73 Tiny					
Turn on TIO and							
Tiny together via	All models	All models	Not support				
Alt + P on USB KB							
Turn on TIO and							
Tiny together via	All models	TIO models	All models				
TIO Power Button							











